

# **Android Terminal**

Home » Newland VB80P

## **Newland VB80P**

#### **Sound Box**

### Secure signature for QR code generation.

Ideal QR Code Generator for Small Merchants. Designed for a seamless QR Code payment experience.

- Large storage memory
- Advanced connectivity
- High-power speakers



#### Specifications —

CPU

32-bit high performance secure processor

Memory

Large capacity memory

Voice Broadcast

**Support preset voice files** 

Loudspeaker

1x loudspeaker, clear and bright sound

Communication

4G, 2G, Wi-Fi

Keypad

1x power button, 1x VOL+, 1x VOL-, 1x function button, 1x reset slot

Peripheral Ports

1xTypeCport,1xSIM

Indicator Light

Status indicator (green, red, blue)

Battery

Li-ion battery, 3.7V 2000mAh

Cable

**USB** charging cable

Installation Methods

Support base and wall-mounted methods

Power Supply

Input: AC100~240V/0.3A 50/60Hz, Output: DC5.0V/1.0A

Amount Screen

Display 6-digit amount, signal, power, time, and the number of receipts on the day

Dynamic Code Screen

2.4-inch color LCD display, support displaying dynamic payment QR code

Environment

Operating temperature: 0°C~50°C (32°F~122°F), Storage temperature: -20°C~60°C (-4°F~140°F), Relative humidity: 5%~95% (Non-condensing)